

RP-DN-36-3500-WHT 36" diameter down light ring fixture

Scaling the fixture size and lumen output.

When absolute photometry (usually LED products) became prominent, like most of the software world, AGI and other programs were not ready to handle them. However, probably the most common way to handle this in AGI is for the user to modify the .ies file.

The testing lab Lumos uses, ITL Boulder produces ies files which have lines in them that look like this:

```
[_ABSOLUTELUMENS] 3362  
TILT=NONE  
168 -1 1 73 1 1 1 -3.005208 -3.005208 0.010417  
1.0 1 52.4
```

Instruct the user to replace the "-1" value with the absolute lumens 3362. Then from there the user can scale the 3362 lumens up or down as necessary. Let me know if you need anything else.