
## Mini Box Cove

3 Sided Pattern Raft Submittal





3.7" 94mm



Architectural Cove 4" minimum offset, 12" typical offset. Can be installed in Cove or Coffer. **Ordering Information** WG-MBC SM CRI/ Model Fixation Pattern Length Power **Driver**<sup>5</sup> Lens Finish Options **CCT**<sup>2</sup> SSD (std) WG-MBC PR<sup>2</sup> 927 LEC SM Х W(std) А L AxB 930 SDC RFC Μ S В AxBxC LREC D010 Н 935 G AxBxAxB 940 **L3DAE** F L3D0E DFPN

#### Luminaire

- Light source positioned for optimum horizontal spread of illumination.
- Light source is not visible from any viewing angle up to and including direct horizontal view.
- Delivers continuous soft wash of directed light to above surface.
- Satin Diffuser for high efficiency and soft edge beam without striations.
- Removable light source sub assembly for simple installation and maintenance.
- High efficiency linear LED in a range of outputs.
- Integral drivers and through wiring.
- Lengths and angles factory cut to exact field dimensions.
- Mitered corners available with continuous illumination.

#### Fixation

■ SM = Surface mount

#### Pattern

- S = Straight run<sup>1</sup>
- PC = Standard patterns coffer 2, 3 or 4 sided with 90° corners<sup>2</sup>
- PR = Standard patterns raft 2, 3 or 4 sided with 90° corners<sup>2</sup>
- PZ = Non-standard patterns and/or corners other than 90°, consult factory<sup>2</sup>

#### Length

 A, B, C = specify inches to the nearest 0.25" (i.e. 72.25") For patterns specify each length (i.e. 2 sided: A x B = 72.25" x 48"; 3 sided: A x B x C; 4 sided: A x B x A x B)

#### **LED**<sup>3</sup>

- L = 3.2W/ft low power (24V)
- M =6.4W/ft medium power (24V)
- H = 10.5W/ft high power (24V)

Customer Approval	Company
Approved	Signature
Approved corrections noted	Print Name
Revise and Resubmit	Date

#### Color / Lumens<sup>4</sup>

90+ CRI minimum (Low/Mid/High)

- 927 = 2700K, (243/450/671 lm/ft)
- 930 = 3000K, (251/464/692 lm/ft)
- 935 = 3500K, (256/474/706 lm/ft)
- 940 = 4000K, (259/478/713 lm/ft)

#### **Driver (remote)**<sup>5</sup>

- X = No driver, ordered separately
- S = Standard driver 120-277V
- D010 = Osram, 10%, 0-10V dimming, 120-277V
- L3DAE = Lutron Hi-lume 1% EcoSystem, 120-277V
- L3D0E = Lutron Hi-lume Premier 0.1% EcoSystem, 120-277V
- DFPN = Lutron Forward Phase 1%, 120VAC

#### Lens

- SSD = Snap On Satin Diffuser (standard)
- SDC = Satin Clear Dust Cover

#### Finish

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

#### Options

- LEC = Left end cap
- REC = Right end cap
- LREC = Left & Right end caps

#### Emergency

- Emergency LED driver available, order separately.
- 1 Standard setup assumes the cove ends at a perpendicular wall and the LED board is setback from the end to minimize light on the perpendicular wall. Contact us for options
- 2 See pattern spec sheet.
- 3 Wattage shown does not include power supplies/drivers.
- 4 Delivered lumens with snap on satin diffuser shown.
- 5 Remote drivers required. See power supply page for details.



whitegoods

410 381 1497 inter-lux.com answers@inter-lux.com Inter-lux reserves the right to make technical changes without notice.



Project Name Fixture Type

PO#

### Mini Box Cove LED

# inter-lux

Submittal Pattern - 3 Sided Raft Corner					Project Name	SO #
					Fixture Type	PO#
System	Qty.	Ov 'A'	erall Leng 'B'	gth 'C'	Customer Approval	Company
1	—				Approved	Signature
2 3					Approved with corrections noted	Print Name
4					Revise and Resubmit	Date

\* overall length of finished mounting surface

