

# EMERGENCY BATTERY BACKUP LED LUMEN OUTPUT

Finelite LED products with emergency battery backup systems use the Bodine BSL722. This system supplies 700ma to 80 LEDs for a minimum of 90 mins.

The predicted lumen output for each product is outlined below:

	3500K LED PRODUCTS	4000K LED PRODUCTS
FIXTURE TYPE	EMERGENCY LUMENS	EMERGENCY LUMENS
HPR 1x1	1239	1285
HPR 1x2 **	1358 **	1433 **
HPR 1x4	1568	1650
HPR 2x2	1644	1730
HPR 2x4	1521	1590
HP-4	1311	1377

\*\* Not currently available for battery backup option