Mini Edgeless Cove


Straight Run Submittal




inter•lux

Fixture Type _____ PO#_____

	and the same of th	





Gypsum Ceiling Mounting 4" minimum offset, 12" typical offset Can be installed in Cove or Coffer

Ordering Information									
WG-MEC	RPT								
Model	Fixation	Pattern	Length	Power ³	CRI/ CCT ⁴	Driver ⁵	Lens	Finish	Options
WG-MEC	RPT	S ¹	A A×B A×B×C A×B×A×B	L M H	927 930 935 940	X S D010 L3DAE L3D0E DFPN	SSD (std) SDC	W (std) B G F	LEC REC LREC LWR RWR

Luminaire

- Light source positioned for optimum horizontal spread of illumination.
- Light source is not visible from any viewing angle up to and including direct horizontal view.
- Delivers continuous soft wash of directed light to above surface.
- Satin Diffuser for high efficiency and soft edge beam without striations.
- Removable light source sub assembly for simple installation and maintenance.
- High efficiency linear LED in a range of
- Integral drivers and through wiring.
- Lengths and angles factory cut to exact field dimensions.
- Mitered corners available with continuous illumination.

Fixation

■ RPT = Recessed plaster trim

Pattern

- S = Straight run¹
- PC = Standard patterns coffer 2, 3 or 4 sided with 90° corners2
- PR = Standard patterns raft 2, 3 or 4 sided with 90° corners2
- PZ = Non-standard patterns and/or corners other than 90°, consult factory²

Length

■ A, B, C = specify inches to the nearest 0.25" (i.e. 72.25") For patterns specify each length (i.e. 2 sided: $A \times B = 72.25$ " x 48"; 3 sided: $A \times B \times C$; 4 sided: $A \times B \times A \times B$)

Power³

- L = 3.2W/ft low power (24V)
- M =6.4W/ft medium power (24V)
- \blacksquare H = 10.5W/ft high power (24V)

CRI/CCT⁴

90+ CRI minimum (Low/Mid/High)

- \blacksquare 927 = 2700K, (243/450/671 lm/ft)
- \blacksquare 930 = 3000K, (251/464/692 lm/ft)
- \blacksquare 935 = 3500K, (256/474/706 lm/ft)
- \blacksquare 940 = 4000K, (259/478/713 lm/ft)

Driver (remote)⁵

- X = No driver, ordered separately
- S = Standard driver 120-277V
- D010 = Osram, 10%, 0-10V dimming, 120-277V
- L3DAE = Lutron Hi-lume 1% EcoSystem, 120-277V
- L3D0E = Lutron Hi-lume Premier 0.1% EcoSystem, 120-277V
- DFPN = Lutron Forward Phase 1%, 120VAC

- SSD = Snap On Satin Diffuser (standard)
- SDC = Satin Clear Dust Cover

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

Options

- LEC = Left end cap
- REC = Right end cap
- LREC = Left & Right end caps
- LWR = Left wall return
- RWR = Right wall return

Emergency

- Emergency LED driver available, order separately.
- 1 Standard setup assumes the cove ends at a perpendicular wall and the LED board is setback from the end to minimize light on the perpendicular wall. Contact us for options
- See pattern spec sheet.
- Wattage shown does not include power supplies/drivers.
- 4 Delivered lumens with snap on satin diffuser shown.
- 5 Remote drivers required. See power supply page for details

Customer Approval	Company
Approved	Signature
Approved with corrections noted	Print Name
Revise and Resubmit	Date

Original Submission Date



Mini Edgeless Cove LED

Submittal - Straight Run

inter•lux

Submittal	 Straight F 	Run	Project Name		SO#
			Fixture Type	F	PO#
System	Qty.	Overall Length 'A'	Customer Appr	oval Company	
1			_ Approved	Signature	
2			Approved with corrections noted	Print Name	
4			Revise and Resubm	it Date	
5					
6			_		
7			_		
8			_		
9			_		
10			*overall length of finis	ned mounting surface	2
power f entrand		rol feed per power feed ance Drilled to fit in field			Wall to Wall
		wall		wall	
	4" blank gear tray	geartray		geartray	4" blank gear tray
		housing		housing	
			▼	Direction	
	-		overall length*——— 'A'		
				will not be illuminated. e hot spot on adjacent wall	
Wall Re		Wall Retu	ırns		End Caps
	,	wall		wall	<u> </u>
	g	ear tray 4" blank gear tray	wall return	gear tray	4" blank gear tray end cap
/_	h	ousing		housing	
	over	all length 'A'	0	verall length	
				'Α'	