

Project:		
Fixture Type:		
Location:		
Contact:		

Two-Light Bath & Vanity

Wall or ceiling mounted • Damp location listed PROGRESS LED



Description:

Create harmony in a variety of environments with Balance's clean design and environmentally friendly architectural styling. Soft acrylic lens and a brushed nickel finish are highlights of the two-light Energy Star LED fixture. Fixtures can be wall or ceiling mounted. Can be installed vertically or horizontally. 3000K, 90+ CRI, 623 lumens per module (source).

Specifications:

- Brushed Nickel (-09) (plated)
- Steel Construction
- White acrylic diffuser
- LED Module is replaceable (part # 93054049)
- · Clean design.
- · Environmentally friendly architectural styling.
- 623 lumens 69.2 lumens/watt per module (source)
- · 3000K color temperature, 90+ CRI.
- · Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting plate for outlet box included
- · 6" of wire supplied
- · ENERGY STAR® qualified

Performance:

Number of Modules	2	
Input Power	9w per module	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Source)	623/69.2 (LM-82) per module	
Lumens/LPW (Delivered)	587.6/32.6 (LM-79)	
CCT	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 °C	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	ENERGY STAR® qualified	

P2092-0930K9

Images:



Dimensions:

Width: 11-1/2" Depth: 3" Height: 5"

H/CTR: 2-1/2" (mounted horizontal)

Glass Width: 2-1/8" Length: 10-7/16" Height: 5"



Two-Light Bath & Vanity





P2092-0930K9

Dimming Notes:

P2092 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron	Nova T	NTELV-300
Lutron	Vierti	VTELV-600
Lutron	Ariadni	AYCL-153P
Lutron	Diva	DVCL-153P
Lutron	Maestro	MAELV-600
Lutron	spacer/sys	stem SPSELV-600
Leviton	Renoir II	AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.