

Project:		
Fixture Type:		
Location:		
Contact:		

# One-Light Outdoor

Wall mounted • Wet location listed PROGRESS LED





## **Description:**

Arrive LED lanterns feature a die-cast aluminum, powder coated frame and heavily textured glass. One-light large wall lantern. 90+ CRI, 3000K, 1,211 lumens 71.2 lumens/watt per module (source). Energy Star.

### **Specifications:**

- Black (-31) (painted)
- Die-cast aluminum Construction
- Clear Seeded glass panels
- LED Module is replaceable (part # 93053641)
- · Die-cast aluminum, powder coated frame.
- · Heavily textured glass.
- 90+ CRI, 3000K, 1,211 lumens. Energy Star.
- · 1,211 lumens 71.2 lumens/watt per module (source)
- · 3000K color temperature, 90+ CRI.
- · Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- · ENERGY STAR® qualified
- · Meets California Title 24 high efficacy requirements for outdoor use only

#### **Performance:**

Number of Modules	1
Input Power	17w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	1211/71.2 (LM-82)
Lumens/LPW (Delivered)	738/41.2 (LM-79)
ССТ	3000 K
CRI	90 CRI
Life (hours)	60,000 (L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Wet location listed
	ENERGY STAR® qualified
	Meets California Title 24 high efficacy requirements
	for outdoor use only

# P6069-3130K9

#### Images:



#### **Dimensions:**

Width: 9" Depth: 10-1/4" Height: 13" H/CTR: 5-3/4"

Glass Width: 0-1/8" Length: 6" Height: 9-1/8"



# One-Light Outdoor



# P6069-3130K9

## **Dimming Notes:**

P6069 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

## **Dimming Controls**

Lutron Nova T NTELV-300

Lutron Vierti VTELV-600

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.