

Application

Remote low voltage transformer, for use with BEGA 12V AC luminaires.

Mounting

Provided with flange for attachment to wall or structure.

Housing

Stainless steel NEMA 3R case, 1/8" thick with stainless

Steel hinges and clasps

Weight: 13 lbs.

Timer and photocell ready

Electrical

Input voltage 120V AC - 3A

Output voltage 12-15V AC

Controlability Non-dimmable

Breakers 1x25A

Frequency 60Hz


Cord 6ft

Type:

BEGA Product:

Project:

Modified:



Low voltage magnetic transformer

		A	B	C
536	300W	13 1/8	6	5 5/8